

Power contactors without handle CX³

from 16 A to 63 A



Dimensions **see e-catalogue**
 Technical characteristics **p. 80**

Conform to IEC/EN 61095
 Space for power supply busbar on top (up to 25 A)

Pack	Cat.Nos	Power contactors with 24 V~ coil		
		2-pole - 250 V~		
1	4 125 03	I max 16 A	Connection 	Type of contact N/C + N/O Number of modules 1
1	4 125 05	25 A		2 N/O 1
		4-pole - 400 V~		
1	4 125 10	25 A		4 N/O 2
1	4 125 09	25 A		2 N/C + 2 N/O 2

Pack	Cat.Nos	Power contactors with 230 V~ coil		
		2-pole - 250 V~		
4	4 125 21	I max 16 A	Connection 	Type of contact N/C + N/O Number of modules 1
10	4 125 23	25 A		2 N/O 2 N/O 1
1	4 125 27	63 A		2
1	4 125 24	25 A		2 N/C 1
		4-pole - 400 V~		
5	4 125 35	25 A		4 N/O 4 N/O 2
1	4 125 41	63 A		3
1	4 125 36	25 A		4 N/C 2
1	4 125 33	25 A		2 N/C + 2 N/O 2

Auxiliaries for contactors CX³

Pack	Cat.Nos	Signalling auxiliaries for contactors		
		Auxiliary changeover switch for all CX ³ contactors Used to signal the position status of the contacts on the product to which it is connected		
		For 1 module contactors 16 A to 25 A Maximum 2 auxiliary devices per contactor Fitted on left-hand side of contactor		
1	4 124 29	I max 5 A	Voltage 250 V~	Contact N/C + N/O Number of modules 0.5
		For 2 module contactors 25 A Maximum 2 auxiliary devices per contactor Fitted on left-hand side of contactor		
1	4 124 30	5 A	250 V~	N/C + N/O 0.5
		For 40 and 63 A contactors Maximum 1 auxiliary device per contactor Fitted on left-hand side of contactor		
1	4 124 31	5 A	250 V~	N/C + N/O 0.5

For detailed dimensions,
see e-catalogue

